

TECHNICAL DATA

Fluke 301A



Key features

- The body weighs only 132g and is 16mm thick, which is light and portable and can be fitted into a pocket
- The slim and thin jaw of only 10mm can easily clamp onto tightly packed wires
- 400A AC range, 0.01A high resolution
- Tests voltage, resistance and continuity
- Tests current frequency and voltage frequency
- Tests capacitance and diodes

Product overview: Fluke 301A

Fluke 301A

The Fluke 301A Clamp Meter has a lightweight and compact body, which allows you to carry it around in your pocket. The slim and thin jaw can easily clamp onto tightly packed wires. The Fluke 301A tests current, voltage, resistance, continuity, frequency (voltage and current), capacitance, and diode, etc.. You can handle more testing needs with it.

Specifications: Fluke 301A

Ordering information



Fluke 301A

Models: Fluke 301A Clamp Meter

Fluke 301A

- Fluke 301A Clamp Meter
- (2) AAA batteries

Fluke 301A+

- Fluke 301A Clamp Meter
- TL75 test lead
- (2) AAA batteries

Note: Fluke 301A is the standard model without test leads.

Fluke 301A+ includes Fluke301A and a TL75 teat lead.

Fluke. *Keeping your world up and running.®*

Fluke Corporation

PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:

In the U.S.A. (800) 443-5853

In Europe/M-East/Africa +31 (0)40 267 5100

In Canada (800)-36-FLUKE

From other countries +1 (425) 446-5500

Fluke Electronics (Malaysia) Sdn Bhd

Suite D-3A-4, Block D

SouthGage Commercial Centre, No2

Jalan Dua Off Jln Chan Sow Lin

55200 KL

Malaysia

Email: info.asean@fluke.com

www.fluke.com/my

©2025 Fluke Corporation. Specifications subject to change without notice.

09/2025

Modification of this document is not permitted without written permission from Fluke Corporation.